

WARNING


PLEASE READ ALL INSTRUCTIONS BEFORE ATTEMPTING INSTALLATION

- To prevent personal injury or product damage only licensed electricians should install.
- To avoid electric shock or component damage disconnect power before attempting installation or servicing.
- This product must be installed in accordance with the national electric code (NEC) and all applicable federal, state and local electric codes and safety standards.
- Disconnect product and allow cooling prior to servicing.
- Any alteration or modification of this product is expressly forbidden as it may cause serious personal injury, death, property damage and/or product malfunction.
- To prevent product malfunction and/or electrical shock this product must be properly grounded.
- This luminaire is designed to operate in ambient temperatures ranging from -40°F to 113°F (-40°C to 45°C) and to be horizontally mounted with the LEDs facing down.
- This product must be installed in accordance with the applicable installation code by a Person familiar with the construction and operation of the product and the hazards involved.
- MIN 167°F (75°C) SUPPLY CONDUCTORS
- This product is not suitable for several special environments, such as places with corrosive gas liquids or high pressure water vapor.

Installation Guide


Hook Installation

1. Tightly screw the hook into the M10 hole on the top of the fixture.
2. Tighten the M4x8 screw to secure the hook.
3. Make electrical connections according to the wiring diagram.




Adjustable Surface Mounting Bracket

1. Secure the mounting bracket to the surface, adjust to the desired angle, and lock the angle adjustment screw.
2. Make electrical connections according to the wiring diagram.




Power & CCT Adjustment Controls

Remove the screw plug at the bottom of the fixture, adjust the dial switch to the desired power level and color temperature to match the application requirements, then reinstall the screw plug as demonstrated below:



Multi-Level Motion Sensor

To install the sensor, remove the screw plug in the middle of the fixture, insert the sensor and tighten clockwise, as demonstrated below:



WIRING DIAGRAM

Brown	Line
Blue	Neutral
Green/Yellow Green	Ground
Purple	
Pink	

Note: Dimming wires are in an external cord.